




Rec'd PCT/PTO 15 JUL 2004 *42*
PCT/GB 2003 / 0 0 0 1 1 1



INVESTOR IN PEOPLE

The Patent Office
Concept House
Cardiff Road
Newport
South Wales
NP10 8QQ

I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein.



In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.

PRIORITY DOCUMENT

SUBMITTED OR TRANSMITTED IN
COMPLIANCE WITH RULE 17.1(a) OR (b)

Signed

AEvens

Dated 4 February 2003


BEST AVAILABLE COPY

Patents Form 1/77

Patents Act 1977
(Rule 16)

The
Patent
Office

17 JAN 02 E688418-8 D0289A
P01/7700 0100-0200939.7



Request for grant of a patent

(See the notes on the back of this form. You can also get an explanatory leaflet from the Patent Office to help you fill in this form)

16 JAN 2002

The Patent Office

Cardiff Road
Newport
South Wales
NP9 1RH

1. Your reference	PJF01256GB		
2. Patent application number (The Patent Office will fill in this part)	0200939.7		
3. Full name, address and postcode of the or of each applicant (underline all surnames)	DenseLight Semiconductors Pte. Ltd. 6 Changi North Street 2 Changi North Industrial Estate, Singapore 498831		
Patents ADP number (if you know it)	8227662001		
If the applicant is a corporate body, give the country/state of its incorporation	Singapore		
4. Title of the invention	An Electroabsorption Modulator		
5. Name of your agent (if you have one)	Gill Jennings & Every		
"Address for service" in the United Kingdom to which all correspondence should be sent (including the postcode)	Broadgate House 7 Eldon Street London EC2M 7LH		
Patents ADP number (if you know it)	745002		
6. If you are declaring priority from one or more earlier patent applications, give the country and the date of filing of the or of each of these earlier applications and (if you know it) the or each application number	Country	Priority application number (if you know it)	Date of filing (day / month / year)
7. If this application is divided or otherwise derived from an earlier UK application, give the number and the filing date of the earlier application	Number of earlier application	Date of filing (day / month / year)	
8. Is a statement of inventorship and of right to grant of a patent required in support of this request? (Answer 'Yes' if: a) any applicant named in part 3 is not an inventor, or b) there is an inventor who is not named as an applicant, or c) any named applicant is a corporate body. See note (d))	YES		

Patents Form 1/77

9. Enter the number of sheets for any of the following items you are filing with this form. Do not count copies of the same document

Continuation sheets of this form

Description 8

Claim(s) 2

Abstract 0

Drawing(s) 4 *TL*

10. If you are also filing any of the following, state how many against each item.

Priority documents

Translations of priority documents

Statement of inventorship and right to grant of a patent (*Patents Form 7/77*)

Request for preliminary examination and search (*Patents Form 9/77*) YES

Request for substantive examination (*Patents Form 10/77*)

Any other documents (please specify) NO

11. For the applicant
Gill Jennings & Every

I/We request the grant of a patent on the basis of this application.

Signature

Date
16 January 2002

12. Name and daytime telephone number of person to contact in the United Kingdom

FINNIE, Peter
020 7377 1377

Warning

After an application for a patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977. You will be informed if it is necessary to prohibit or restrict your invention in this way. Furthermore, if you live in the United Kingdom, Section 23 of the Patents Act 1977 stops you from applying for a patent abroad without first getting written permission from the Patent Office unless an application has been filed at least 6 weeks beforehand in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or any such direction has been revoked.

Notes

- If you need help to fill in this form or you have any questions, please contact the Patent Office on 0645 500505.*
- Write your answers in capital letters using black ink or you may type them.*
- If there is not enough space for all the relevant details on any part of this form, please continue on a separate sheet of paper and write "see continuation sheet" in the relevant part(s). Any continuation sheet should be attached to this form.*
- If you have answered 'Yes' Patents Form 7/77 will need to be filed.*
- Once you have filled in the form you must remember to sign and date it.*
- For details of the fee and ways to pay please contact the Patent Office.*

AN ELECTROABSORPTION MODULATOR

Field of the Invention

The present invention relates to a high speed modulating device for use in optical communication systems, and in particular a chirp-compensated electroabsorption modulator.

Background to the Invention

The continuing growth in the volume of information to be transported by optical communication systems is placing increasing demands on the speed and bandwidth of these systems. In order to satisfy this need optical components capable of dealing with the higher data rates and broader bandwidth are required. This includes the optical fibre used as the transport medium and components such as the optical modulator, used to encode data onto an optical signal.

A number of techniques have been employed to produce fast optical modulators, including a Mach-Zehnder Interferometer (MZI) type arrangement. However, the electroabsorption modulator (EAM) has emerged as an alternative, and often preferred choice, due to its low voltage requirements and relatively compact physical dimensions. Electroabsorption modulators have already been implemented in 10Gb/s optical fibre based communication systems. Like the MZI modulator, the EAM usually comprises a waveguide section for optical confinement, in order to be compatible with fibre systems. The EAM can be integrated with a laser source in a single module or may be fabricated as a stand alone device.

The EAM operates via an electric field induced change in the absorption spectrum, the so-called electroabsorption (EA) effect. A number of very fast physical mechanisms may be involved in this spectral shift, including the linear and quadratic Stark effect. In order to enhance the performance of such devices, multiple quantum well (MQW) structures have been included, thereby taking advantage of the quantum-confined Stark (QCS) effect. As a consequence, a small applied electric field can induce a large change in absorption at a particular wavelength. For example, the application of a reverse bias voltage of a few volts to a MQW based EAM results in a bandgap shift to longer wavelengths and a device extinction ratio as high as 20dB.

Although the underlying mechanism is very fast, the speed of response of a conventional lumped-element EAM to an electrical driving signal is limited by intrinsic and

stray capacitance, thereby limiting the useful modulation bandwidth. One approach to tackling this problem is the use of a shorter EAM waveguide to reduce device capacitance. However, this approach tends to compromise modulation efficiency and extinction ratio. Figure 1 shows an example of one of the more successful lumped EAMs, where a short MQW based EAM is integrated with transparent input and output waveguides and fabricated on an InP:Fe substrate to reduce the stray capacitance.

A more successful technique for increasing the useful modulation bandwidth of an EAM makes use of the travelling wave effect that arises when a driving microwave signal copropagates alongside an optical signal confined within the EA region of an EAM.

10 The so-called travelling-wave EAM (TW-EAM) has been investigated experimentally and shown to exhibit superior performance to the lumped element EAM. In a typical TW-EAM an electrode structure is employed that provides a transmission line for the driving microwave signal to propagate alongside the optical signal. This transmission line ensures good overlap of the modulation field with the EA region, permitting high speed operation with good modulation characteristics. An example of a known TW-EAM is shown in Figure 2.

A major challenge associated with the TW-EAM is the accurate velocity matching of the optical and microwave signals over a broad bandwidth. The fundamental sources of temporal mismatch of the two signals are the respective lengths of the waveguide and transmission line and also the resistance to signal propagation, as measured by the modal refractive index and line impedance for the optical and microwave signals, respectively. One approach to achieving velocity matching is the use of a TW-EAM comprising several discrete EAM regions, such that a transmission line can be fabricated which overlaps these regions but where the microwave signal follows a longer path than the optical signal, thereby compensating for the faster speed of propagation.

However, even with adequate velocity matching, a further problem associated with the TW-EAM is the broadening of an optical signal's bandwidth during propagation through the TW-EAM. The problem can also occur for the lumped EAM, but is of less importance at the modulation frequency typically used. The problem manifests itself as an apparent difference in the speed of propagation of the different wavelength components contained within the encoded optical signal, a characteristic known as chirp. The origin of this problem is an unwanted phase modulation of the optical signal that can accompany the intended amplitude modulation. When a driving electric field is applied to an EAM, the resulting change in the active material's bandgap leads to a change in

absorption, which effects the amplitude modulation of the optical signal. However, associated with the change in the material bandgap is a change in the material refractive index, which results in the unwanted phase modulation of the optical signal. As the broadened signal leaves the EAM and enters an optical communications network, the problem is compounded still further by the inherent dispersion exhibited by optical fibre in the network. The wavelength components in the broadened spectrum of the optical signal each experience a different refractive index in the fibre leading to even further broadening of the spectrum.

As a result of signal chirp, the integrity of data encoded on an optical signal may be compromised. For example, data encoded digitally may be represented by a series of temporal spikes which, in the presence of chirp, may develop a pedestal that blurs the distinction between individual bits of data. This can be particularly troublesome when the data stream comprises several signals from different sources that have been multiplexed by an optical time division multiplexing (OTDM) system. Similarly, a signal with a broadened bandwidth may result in data integrity being compromised, if multiplexed with other signals in a wavelength division multiplexing (WDM) system.

Thus, the elimination or negation of chirp in EA modulators, especially the TW-EAM, is of key importance for high bit-rate, long haul systems, particularly for the 40GHz and above required by next generation optical communication systems.

20

Summary of the Invention

According to one aspect of the present invention, an electroabsorption modulator (EAM) comprises a first EAM section optically coupled to a second EAM section, a transition wavelength in the electroabsorption (EA) spectrum of the first EAM section, at which absorption changes substantially, being different to a transition wavelength in the EA spectrum of the second EAM section.

Preferably, the first EAM section and second EAM section are driven, with a phase difference between them, by separate radio frequency (RF) signals generated in dependence on a common modulating RF signal. Preferably, the phase difference is 180° such that the first EAM section and second EAM section are driven in anti-phase in dependence on the common modulating RF signal.

In the present invention, an EAM comprises a first and second EAM section that are optically coupled and driven in anti-phase in dependence on a common modulating RF signal. An optical signal passing through the EAM, with a wavelength similar to the EA

transition wavelength of one of the first and second EAM sections, will be amplitude modulated by that EAM. At the same time, the other of the first and second EAM sections will preferably be substantially transparent at the wavelength of the optical signal, both in the presence or absence of the RF signal. Thus, no amplitude modulation will be imposed on the optical signal by this EAM section. In this way, the amplitude of the optical signal may be modulated by one of the first and second EAM sections whilst being substantially unaffected by the other EAM section.

However, due to the dispersion characteristics of an EAM, an optical signal passing through an EAM will experience phase modulation, leading to signal chirp and associated spectral broadening, even when the wavelength of the optical signal is different to the EA transition wavelength of the EAM. The amount of phase modulation (chirp) imparted to the signal will depend not only on the dispersion characteristics of the EAM material but also on the EAM length and the strength of the driving RF signal. By driving two EAM sections in anti-phase, in accordance with the present invention, an amplitude modulated optical signal may be generated with a controlled amount of chirp, including positive, negative or zero chirp.

Therefore, in an EAM according to the present invention, any unwanted phase modulation accompanying the amplitude modulation of an optical signal by one of a first and second EAM sections, may be wholly or partially compensated for by phase modulation applied, in anti-phase, by the other of the first and second EAM sections. If the length and dispersion characteristics of the first and second EAM sections are similar, the resultant amount of chirp will be small and may be fine-tuned by the relative strength of the RF driving signals applied to the two EAM sections.

Preferably, a fast optical chirp detection system is employed to provide an error signal for feedback to the driving circuitry for the RF signals, thereby providing for dynamic correction of signal chirp in the EAM. In the absence of such a system a predetermined signal is applied to the two EAM sections, based on prior testing of the electroabsorptive dispersion characteristics of the two EAM sections.

Generating an amplitude modulated optical signal with a predefined amount of positive or negative chirp may be desirable in the dispersion management of optical networks. An example would be the "pre-compensation" of group velocity dispersion or non-linear phase modulation that may affect the optical signal during propagation through other components in the optical network.

Although the present invention may comprise a discrete first and second EAM

section, it is preferred that the invention comprises a first EAM section integrated with a second EAM section. Preferably, the first and second EAM sections are monolithically integrated on a common semiconductor substrate. Preferably, the substrate comprises an indium phosphide (InP) based material, as this allows integration with other devices,
5 such as a laser diode.

There are a range of materials and mechanisms available for the fabrication of an EAM.

Preferably, the first and second EAM sections comprise a multiple quantum well (MQW) structure. Preferably, over the desired range of operational optical wavelengths,
10 the MQW structure is optimized to be electroabsorbing in one EAM section and transparent in the other EAM section.

Transparency may be achieved by ensuring the EAM material exhibits a large bandgap. Appropriate tailoring of this bandgap may be achieved by selective epitaxial growth or by use of a quantum well intermixing (QWI) process. QWI may also be used to
15 smooth the transition region between the electroabsorbing EAM section and the transparent EAM section in a monolithically integrated version of the present invention.

The EAM according to the present invention may be of the lumped type or may be of the travelling wave (TW) type. In each case it is preferred that the EAM comprises a first EAM section and a second EAM section of the corresponding type. Typically a
20 lumped EAM is used at a lower modulation frequency of 10 Gbit/s, where signal chirp due to optical phase modulation is not a significant problem. Signal chirp is, however, a problem at frequencies of 40 Gbit/s and above where the travelling-wave EAM (TW-EAM) is commonly used.

The present invention thus provides an EAM, preferably a TW-EAM, for high-
25 speed, broad-band amplitude modulation of an optical carrier signal with zero signal chirp, suitable for long haul operation where optical fibre dispersion may become significant. Furthermore, a controlled amount of positive or negative chirp may be imparted to the modulated signal for the pre-compensation of such dispersion.

According to another aspect of the present invention, an optical device for optical
30 time division multiplexing or demultiplexing comprises an EAM in accordance with the one aspect of the present invention.

Brief Description of the Drawings

Examples of the present invention will now be described in detail with reference

to the accompanying drawings, in which:

Figure 1 is a schematic of a known EAM;

Figure 2 is a top view of a known TW-EAM;

Figure 3 shows a schematic of a TW-EAM with chirp-compensation, in accordance
5 with the present invention; and,

Figure 4 shows the electroabsorption spectrum for the two regions, parts A and B, of the TW-EAM shown in Figure 4.

Detailed Description

10 The present invention provides an apparatus for modulating an optical carrier signal, with a controlled amount of signal chirp, by means of two optically coupled EAM sections, one of which is electroabsorbing and the other of which is optically transparent at the optical signal wavelength, the two EAM sections being driven in anti-phase in dependence on a common modulating RF signal.

15 Typically, an EAM is optically transparent at a wavelength longer than its EA transition wavelength. Typically, therefore, the EA transition wavelength of the electroabsorbing EAM section will be longer than that of the transparent EAM section. By applying a suitable driving RF signal to the electroabsorbing EAM section, an optical carrier signal passing through the EAM may be amplitude modulated. Any unwanted
20 phase modulation accompanying the amplitude modulation may be compensated for by phase modulation applied in anti-phase to the optical signal by means of the transparent EAM section.

Figure 3 shows a schematic of an EAM in accordance with the present invention. The EAM is of the travelling-wave type and therefore comprises two TW-EAM sections, monolithically integrated on a common substrate. The electroabsorbing and the
25 transparent parts of the TW-EAM are denoted as Part A and Part B, respectively. The core components of each of the TW-EAM sections are an optical waveguide for light confinement, including a MQW structure, and a strip transmission line located above the optical waveguide. Both transmission lines are terminated by a suitable resistive load to
30 avoid significant reflection of the driving RF signal, which may lead to timing jitter and distortion of the modulated optical signal.

The MQW structure in Part A is optimized to be electroabsorbing at the desired operational optical wavelength. The optical transparency of Part B is achieved by increasing the bandgap of the MQW structure, either by selective epitaxial growth or by

post growth modification using a QWI process. The bandgap in Part B can be engineered such that the EA transition wavelength is sufficiently below the operational wavelength for optical transparency, but close enough that a sufficient amount of dispersion can be experienced by an optical signal to facilitate chirp compensation. To smooth the transition at the interface between Parts A and B, and reduce optical losses, a QWI process may be applied to the MQW structure in the region of the interface.

A differential amplifier is employed to drive the two TW-EAM sections in anti-phase with a common modulating RF signal. A single modulating signal is fed to the differential amplifier, which produces two copies of the original signal with a 180° phase shift between them, but which are otherwise time-synchronized. A suitable time delay may be applied to the signal for driving the transparent TW-EAM section so that the modulated optical and RF signals are appropriately time-synchronized in the TW-EAM. Furthermore, as shown in Figure 3, a variable attenuator is employed to adjust the strength of the RF signal applied to Part B, and thereby fine-tune the amount of compensating phase modulation.

Figure 4 shows a typical electroabsorption spectrum for Parts A and B of the device depicted in Figure 3. The desired operational wavelength is within the electroabsorption transition region of Part A. Therefore, as shown, in the absence of an applied electric field (solid line) the EA region of Part A is substantially transparent. When an RF electric field is applied (broken line), the EA region of Part A becomes absorbing, thus permitting amplitude modulation of an optical carrier signal.

In addition to the change in the absorption spectrum, when an RF signal is applied, there is an associated change in the dispersion characteristics or refractive index spectrum (not shown here). It is this change which gives rise to the unwanted phase modulation of the optical carrier signal and hence signal chirp. A similar change in the dispersion characteristics of the EA region of Part B occurs when the RF signal is applied, a feature which can be used to compensate for the phase modulation acquired in Part A. As can be seen from Figure 4, the EA transition wavelength of Part B is significantly shorter than the desired optical wavelength. Therefore, even in the presence of an applied RF electric field, Part B remains substantially transparent and contributes no amplitude modulation to the optical signal.

If the length and dispersion characteristics of parts A and B are very similar, accurate compensation, and hence zero signal chirp, can be obtained by driving the two regions with an RF signal of similar strength, but in anti-phase. In the example of Figure

3, a weaker signal is required to drive Part B to achieve chirp compensation and is achieved by appropriate adjustment of the variable attenuator. By setting the variable attenuator to values above and below that required for compensation, a controlled amount of positive or negative chirp may be obtained. If a stronger signal is required to drive Part B to compensation or beyond, the variable attenuator can be replaced by an amplifier. However, it is preferable to supply a stronger RF signal to the differential amplifier and add a variable attenuator to the circuitry connecting to the transmission line of Part A.

The ability to generate an amplitude modulated optical signal with a small amount of controlled chirp may be helpful in the dispersion management of optical networks. In optical communication systems where high data rate optical signals are transmitted over long haul distances, even small amounts of dispersion in the optical fibre can have a significant cumulative effect. Therefore, a modulated optical signal "pre-chirped" with the correct amount of oppositely signed chirp could be used to negate the effects of fibre dispersion in long haul transmission.

In the example of Figure 3, the amplitude modulating TW-EAM section precedes the transparent TW-EAM section, in terms of the direction of light propagation. However, the order of the two TW-EAM sections could be reversed. Indeed the overall EAM could comprise an amplitude modulating EAM section optically coupled to two transparent EAM sections located either side of the amplitude modulating EAM section, each driven independently by a common RF signal.

Typically, in all these devices, a fixed predetermined signal strength (voltage) is applied to the EAM sections based on prior testing and knowledge of the dispersion characteristics of the EAM sections, in order to obtain the desired signal chirp. However, if a very fast optical detection system is able to monitor the amount of signal chirp, this can provide an error signal. Such a signal, when fed back to the RF driving circuitry, can provide for dynamic stabilization of the total signal chirp, including precise compensation or zero chirp.

Thus, the present invention provides an EAM suitable for high-speed, broad-band amplitude modulation of an optical carrier signal with zero signal chirp. A travelling-wave embodiment of the device is particularly suitable for high bit-rate, long haul operation where optical fibre dispersion may become significant. Furthermore, a controlled amount of positive or negative chirp may be imparted to the modulated signal for the pre-compensation of such dispersion.

CLAIMS


1. An electroabsorption modulator (EAM), comprising a first EAM section optically coupled to a second EAM section, a transition wavelength in the electroabsorption (EA) spectrum of the first EAM section, at which absorption changes substantially, being different to a transition wavelength in the EA spectrum of the second EAM section.
2. An EAM according to claim 1, wherein the first EAM section and second EAM section are driven, with a phase difference between them, by separate radio frequency (RF) signals generated in dependence on a common modulating RF signal.
3. An EAM according to claim 2, wherein the phase difference is 180° such that the first EAM section and second EAM section are driven in anti-phase in dependence on the common modulating RF signal.
4. An EAM according to claims 2 or 3, wherein the amplitudes of the RF signals driving each of the first EAM and second EAM sections are controlled independently.
5. An EAM according to any of the preceding claims, wherein one of the first EAM and second EAM sections is substantially transparent at a wavelength at which the other of the first EAM and second EAM sections is substantially electroabsorptive.
6. An EAM according to any of the preceding claims, wherein the sign and magnitude of phase modulation imparted to an optical signal propagating through the EAM is determined by the lengths of the first EAM and second EAM sections.
7. An EAM according to claim 6, wherein the sign and magnitude of the phase modulation imparted to the optical signal is further determined by the amplitudes of the RF signals driving each of the first EAM and second EAM sections.
8. An EAM according to claim 7, wherein the amplitudes of the RF signals driving the first EAM and second EAM sections are determined in dependence on an optical device monitoring the phase modulation imparted to the optical signal.

9. An EAM according to any of the preceding claims, wherein the first EAM and second EAM sections are integrated on a common substrate.

10. An EAM according to any of the preceding claims, wherein at least one of the first EAM and second EAM sections comprises a multiple quantum well (MQW) structure.


11. An EAM according to any of the preceding claims, wherein each of the first EAM and second EAM sections comprise a travelling wave EAM (TW-EAM).

12. An optical device for optical time division multiplexing comprising an EAM according to any of the preceding claims.



PRIOR ART

Figure 1



PRIOR ART

Figure 2




Figure 3




Figure 4

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

☐ BLACK BORDERS

☐ IMAGE CUT OFF AT TOP, BOTTOM OR SIDES

☐ FADED TEXT OR DRAWING

☐ BLURRED OR ILLEGIBLE TEXT OR DRAWING

☐ SKEWED/SLANTED IMAGES

☐ COLOR OR BLACK AND WHITE PHOTOGRAPHS

☐ GRAY SCALE DOCUMENTS

☒ LINES OR MARKS ON ORIGINAL DOCUMENT

☐ REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY

☐ OTHER: _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.